

Volcano



Model : VA-450 **4 Channel Amplifier**



SPECIFICATIONS

Stereo@ 4 Ohm

Stereo@ 2 Ohm

Bridge @ 4 Ohm

Frequency Response

Hi-pass Frequency

Low-pass Frequency

S/N Ratio

Input Sensitivity

High Level Input Sensitivity

Bass Boost(50Hz)

Max. Peak Current

Idle Current

Dimension (W x D x H) cm.

VA-450

4 X 57W

4 X 81W

2 X 160W

10Hz - 20KHz

65 Hz - 350kHz

65 Hz - 400kHz

>105dB

160mV - 5.2V

10dB

70 A @ 320 W

0.82 A

30 x 22 x 5.5